


Swiitech Wireless 2-in- 1 Adapter **User Guide**

Thank you for choosing the Swiitech TR-01 Wireless 2-in-1 Adapter. Please read this guide carefully and keep it in a safe place for future reference. If you need any further assistance, please contact our customer support team at support@iswiitech.com

Package Contents


2 3.5mm Audio Cable ③ 3.5mm Female to 2 RCA Male Cable 4 USB Charging Cable ⑤ User Guide 6 3.5mm Audio Plug



Product Diagram

1) Volume - / Previous Track ② Volume + / Next Track 3 Transmitter Mode Switch: Receiver (RX)/Transmitter (TX)

(4) LED Indicator 6 Charging Port 7 3.5mm Audio Port



Specifications

Bluetooth® Profile	A2DP / AVRCP	
Audio Codec	SBC / aptX	
Range	33 ft / 10 m	
Charging Power	DC 5V	
Battery Capacity	350mAh	
Working Time	Approx. 20 hours	
Charging Time	2 hours	
Dimensions (L x W x H)	156 x 108 x 18mm	
Weight	97 g	

Control Functions

Function	Operation
Power On / Off	Press and hold the Power Button for 3 seconds
Pairing	After device is powered on, press the Power Buttor twice to start pairing
Mode Switch	Choose between Transmit (TX) and Receive (RX)
Play / Pause	In RX mode, press the Power Button once to play / pause music
Volume + / -	In RX mode, press and hold the Volume + / - Buttor
Next / Previous Track	In RX mode, press the Volume + / - Button once

LED Indicators

LED Indicator	Status
Solid Red LED	Charging
LED Off	Fully charged
Flashing Red and Blue	Pairing in TX / RX mode
Flashing Red	Low battery
Solid Blue LED	Successfully paired
LED flashes blue once per second	In TX mode, adapter is powered on but not paired with a Bluetooth® device
LED flashes blue twice every three seconds.	In RX mode, adapter is powered on but not paired with a Bluetooth® device

Basic Operation

When the mode switch is turned to "TX" the adapter is in transmitting mode. When the mode switch is turned to "RX" the adapter is in receiving mode.

Switching between TX and RX modes can only be successfully done after the adapter has been turned off for 5 seconds. Please do not change modes when the adapter is turned on.

When turning the adapter off to switch modes, the control chip needs 5 seconds to completely power down. After 5 seconds, you may change modes and power up the adapter again.

Press and hold the power button for 3 seconds, the adapter will automatically turn on and enter the pairing state.

During this time, the red and blue lights will alternately flash. If the adapter discovers a previously connected device, it will connect. If not, it will wait for a new device to try to connect to it (see "How to clear pairing history"

If the LED does not flash red and blue, please double-click the power button to enter pairing mode.

Power Off

Manual Power off Press and hold the power button for 3 seconds. The red indicator LED will light for 1 second and then the adapter will shut off.

Automatic Shut-down:

① In RX mode, after the adapter is turned on, it enters the pairing and connection state. If there is no connection after 5 minutes, the product will automatically shut down.

②When the battery power is lower than 3.1V, the product will automatically

How to clear pairing history

If the adapter is unable to pair with any Bluetooth devices indicated by a contual flashing of the red and blue LEDs - please kindly follow the steps below to clear its pairing history:

1. Press and hold the power button for 3 seconds to turn the adapter off.

2. Wait 5 seconds, then slide the mode selector switch to the mode you were not just using.

3. Turn the adapter back on for a moment, then quickly back off again.

4. Wait for 5 seconds again, then switch back to the original mode. The pairing

5. Now you can turn on the adapter and connect your Bluetooth devices.

Charging

history will be cleared.


1. Use a micro USB cable and connect the adapter to any active USB port 2. The LED indicator will turn red when charging. It will automatically turn off when the device is fully charged.

• We recommend charging the unit for at least 2 hours before using it for the

• When the adapter needs to be used continuously for longer than the battery lasts, it can be connected to a charging power supply (DC 5V ≥ 300mA, Low battery power or poor power quality may lead to low-quality sound). Connect the charging power supply first and then turn on the adapter.

it is not recommended to use this function frequently when charging, because it may affect the service life of the battery

How to Use - Pairing in TX mode



1. Set the adapter to TX mode and connect it to your non-Bluetooth® device (television, music player, etc...) using a 3.5 mm audio cable/plug. Insert one end into the audio port of the adapter, and the other end into the audio out jack of the Non-Bluetooth® device.

2. Place your Bluetooth® audio receiving device, (earphones, speakers, etc...) within a 3 feet / 1 meter range and power it on. Set it to pairing mode.

3. Press and hold the adapter's power button for 3 seconds to turn it on. Tap the power button twice to enter pairing mode (the light will flash red and blue). After approximately 10 seconds, pairing will complete.

4. After the connection is successful, the blue indicator light will

A 3.5 mm female to 2 RCA male cable is suitable for connecting the adapter to a TV without a 3.5mm audio output jack. This cable is included in the package.

How to pair with two Bluetooth devices at the same time - in TX mode

In TX mode, the adapter is able to pair with two Bluetooth® stereo earphones/speakers at the same time. 1. Follow the previous instructions in the "Pairing" section to pair the adapter with your first device.

2. Tap the adapter power button twice to enter pairing mode, and turn on the second Bluetooth. Make sure this device is also in pairing mode.

3. Put the adapter and the second device close together and the pairing

will be completed.


• To ensure that the adapter will successfully pair with the two Bluetooth devices you want to connect to, make sure there are no other Bluetooth devices within 10 meters of the adapter, especially those that have previously paired with your Bluetooth headset.

• When you pair with two devices, both can play music at the same time.

Button operations in TX mode

- When connected to one Bluetooth headset In TX mode, shortpress the power button. The music will pause for 0.5 seconds, which is part of normal operation.
- When connected to two pairs of headphones, short press the power button, there will be no pause seconds.
- Other buttons are unavailable in transmitter mode.

How to Use - Pairing in RX mode:



1. Set the adapter to RX mode and use a 3.5mm audio cable/plug inserted into the audio port of the adapter. Insert the other end into your Non-Bluetooth® audio receiving device (speakers, headset, etc...)

2. Press and hold the adapter's power button for 3 seconds to turn it on. Tap the power button twice to enter pairing mode. The adapter's light will flash

3. Activate the Bluetooth® function on your transmitting device (phone, tablet, etc...) and search for nearby Bluetooth® devices.

4. Find "TR-01" in the search results and tap on it to connect. Once connected, the LED indicator on the adapter will turn solid blue.

Pair with two Bluetooth devices at the same time - in RX mode:

In RX mode, the adapter is able to pair with two Bluetooth® devices at the same time.

1. Follow the previous instructions in the "Pairing" section to pair the adpater with your first device.

2. Tap the adpater power button twice to enter pairing mode and turn on the Bluetooth of the second device, Find "TR-01" in the search results and tap

3. After a successful connection, the TR-01 adapter is paired with both

• Only one device can play music through the adapter at any time. You have to stop the music one the one device to play on the other.

• In RX mode, you can operate the volume buttons on the adapter to

Button operations in RX mode

1. Play/Pause (RX): When playing music, short press the "Power button" to pause/play the music.

2. Volume up (RX): When playing music, long press the "+" button.

3. Volume down (RX): When playing music, long press the "-" button

4. Previous song (RX): When playing music, short press the "◄•" 5. Next song (RX): When playing music, short press the "▶\"

In the RX mode, some Android phones will have the problem of playing music and video at the same time. This is because of the compatibility of individual Android phones. This will not happen as long as the volume up/down button is not pressed while the video is playing.

PRECAUTIONS

1. When power is low or the adapter is not used for a long time, it should be charged before use to prevent the product from working abnormally or receiving battery damage.

2. Bluetooth signals will be blocked and absorbed by surrounding objects. For the best sound quality, try to use the adapter in a direct line-of-sight with your connected device.

3. The adapter has a built-in lithium battery, please charge frequently when using it.

4. Please keep the adapter away from water or other liquids to avoid

5. If you have any problems, please feel free to contact us at

support@iswiitech.com and we will be happy to help you.

The Bluetooth® word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by Sunvalleytek International Inc. is under license. Other trademarks and trade names are those of their respective owners.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct

- Reorient or relocate the receiving antenna. - Increase the separation between the equipment and receiver. -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -Consult the dealer or an experienced radio/TV technician for help

the interference by one or more of the following measures:

This device complies with Part 15 of the FCC Rules. Operation is subjectto the following two conditions:

Changes or modifications not expressly approved by the party responsible

for compliance could void the user's authority to operate the equipment.

(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

WEEE Compliance

Correct Disposal of This Product (Waste Electrical & Electronic Equipment)

(Applicable in countries with separate collection systems) This marking on the product, accessories or literature indicates that the product and its electronic accessories should not be disposed of with other household waste at the end of their working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate these items from other types of waste and recycle them responsibly to promote the sustainable reuse of

Household users should contact either the retailer where they purchased his product, or their local government office, for details of where and how they can take these items for environmentally safe recycling. Business users should contact their supplier and check the terms and conditions of the purchase contract. This product and its electronic accessories should not be mixed with other commercial wastes for disposal.

Swiitech

support@iswitech.com

CE S MADE IN CHI

SIZE: 100x150mm

材质: 128g铜版纸, 单黑印刷, 不做表面处理, 折叠 (手风琴式)